


SMA8100-0178	SMA Jack Crimp	50Ω
	<u>-</u>	



Parts	Material	Plating (Micro-inch)
Ferrule	Brass	Gold 5 Over Nickel 50 Over Copper 50
Contact Pin	Beryllium Copper	Gold 20 Over Nickel 50 Over Copper 50
Insulator	Teflon	
Body	Brass	Gold 5 Over Nickel 50 Over Copper 50

Weight: 1.65 g

Suitable Cables: RG178, RG196, RG178-FEP

This part number complies with RoHS.

Notice: JYEBAO reserves the right to make modifications deemed appropriate.



CABLE ASSEMBLY INSTRUCTION SMA8100-0178 JYE BAO CO., LTD. В С D Ε 0 -FERRULE FERRULE INSULATOR CONTACT PIN **BODY** ASSEMBLY INSTRUCTION DIAGRAM Step 1: STRIP AS SHOWN. [.161] 2.5 [.098] Step 2: SLIDE FERRULE "A" OVER CABLE. Step 3: WRAP THE BRAIDING OVER FERRULE "A". Step 4: SLIDE CENTER CONDUCTOR INTO FERRULE "B" AND TEFLON "C". Step 5: PUT PIN "D" ON CONDUCTOR AND SOLDER IN "X". Step 6: PUT PREPARED CABLE INTO CONNECTOR "E" AND CRIMP IN "Y".

This part number complies with RoHS.

Notice: JYEBAO reserves the right to make modifications deemed appropriate.